



BLE  
(1 Output Line Extender)



MB  
(2 or 3 Output Mini Bridger)

## ASEM™ Complete Stations & RF Modules 1218 MHz For GI/Motorola® BLE & MB

The ACI ASEM 1.2G replacement upgrade RF modules for the Moto BLE and MB are designed to work up to a high forward output of 57 dBmV. The return bandwidth split can be easily changed from 42 to 85 or 204 MHz with the use of field conversion kits. ACI's patented DSIM advanced technology keeps both the forward and return signals stable and reliable over extreme temperature swings. Having return band stabilization over temperature has become much more important as return band is increased to 204 MHz. Having the increased return gain of 28 dB enables these amplifiers to drop into existing designs from 750 MHz to 1 GHz.

### Features

- ◆ Drop-in 1.2G replacement RF modules for Motorola® Starline® MB Mini-Bridger and BLE Line Extender
- ◆ Easy upgrade to 85/105 or 204/258 MHz return bandwidth.
- ◆ -20.0 dB directional coupler test points
- ◆ Complete stations available
- ◆ RoHS Compliant
- ◆ Patented DSIM® Technology (programmable AGC)
- ◆ Increased reliability with higher surge protection
- ◆ DSIM controlled return band AGC
- ◆ Pad adjustable forward and return EQ's
- ◆ DSIM Android & Apple iOS setup applications



## Station Parameters 42/53

STATION PARAMETERS:		1218 MHz 42-53 MHz Split		ASEM For Motorola 1218 MHz MB & BLE	
		CONDITIONS	UNITS	SPECIFICATIONS	
Housing passband			MHz	5 to 1218	
Input current capacity	Any port, worst case		Amp	15	
Hum modulation	Time domain @ rated current above		-dBc	65 @ 5-42 MHz 65 @ 54-1218 MHz	
Return loss	Any port, worst case		dB	16.0	
<b>Test Points</b>					
Frequency range			MHz	5 to 42 (Reverse) / 54 to 1218 (Forward)	
Test point type	Directional coupler		N / A		
Test point level	Forward & reverse		-dB	20.0	
Test point accuracy	Forward & reverse		±dB	0.75	
<b>Station Slope</b>				MB (Mini Bridger)	BLE (Line Extender)
Operational slope (Tilt)	@ 54 / 550 / 1218 MHz		dB	0 / 8.1 / 19.0	0 / 8.1 / 19.0
Slope control type	Cable equalizers		dB	Pad Adjustable EQ's	
Slope control range	Includes cable equivalent		dB	-12.0 to +22	
Slope control steps	Equalizer value steps		dB	1.0	
<b>Station Group Delay</b>					
Group delay	Channel 2 (Std)	nSec / 3.58 MHz		37	
Group delay	Channel 3			16	
Group delay	Channel 4			10	
Group delay	Channel 5 & up			4	
<b>AGC</b>					
Pilot channel type	Up to 1002 MHz		N / A	DSIM-A Single Pilot Channel AGC Analog or QAM	
Compensation range			dB	System compensation input change +4/-8 @ 1218 MHz	
Accuracy			±dB	0.5	
Nominal loss	@ 77 °F (25 °C)		dB	6.25	
<b>Configuration</b>				MB (Mini Bridger)	BLE (Line Extender)
<b>Operational Specifications</b>					
Station flatness	Normalized w / 0 dB slope		±dB	0.50	0.30
Gain - Port 2 (W/DSIM)	+1.0 / -0 @ 1218 MHz		dB	48.0	42.0
Gain - Port 3 (W/DSIM)			dB	-	-
Gain - Port 4 (W/DSIM)			dB	48.0	-
496 MHz analog channel loading, 79 channels + 660 MHz digital channel loading, 256 QAM at -6 dBc relative to its associated visual carrier					
<b>Station Referenced Output Levels</b>				MB (Mini Bridger)	BLE (Line Extender)
Port 2	@ 54 / 550 / 1218 MHz		dBmV	38.0 / 46.1 / 57.0	
Port 3				-	
Port 4				38.0 / 46.1 / 57.0	
Reference output slope (Tilt)	54-1218 MHz		dB	19.0	19.0
<b>Station Noise Figure</b>					
Noise figure (W/1 dB for input EQ loss)	Typ. @ 54 to 1002 MHz		dB	9.0	9.0
	Typ. @ 1218 MHz		dB	9.5	10.5
<b>Station Distortions (Worse Case)</b>					
Composite Triple Beat (CTB)			-dBc	67	67
Cross Modulation (XMOD)			-dBc	65	64
Composite Second Order (CSO-)	(Vc +0.75 & -1.25 MHz)		-dBc	67	67
Composite Second Order (CSO+)	(Vc +1.25 MHz)		-dBc	67	67
MER			dB	≥40	≥40
BER			N / A	≤ 1 x 10 <sup>-9</sup>	≤ 1 x 10 <sup>-9</sup>

# Station Parameters 85/105

STATION PARAMETERS:		1218 MHz 85-105 MHz Split		ASEM For Motorola 1218 MHz MB & BLE	
		CONDITIONS	UNITS	SPECIFICATIONS	
Housing passband			MHz	5 to 1218	
Input current capacity	Any port, worst case		Amp	15	
Hum modulation	Time domain @ rated current above		-dBc	65 @ 5-85 MHz 65 @ 105-1218 MHz	
Return loss	Any port, worst case		dB	16.0	
<b>Test Points</b>					
Frequency range			MHz	5 to 85 (Reverse) / 105 to 1218 (Forward)	
Test point type	Directional coupler		N / A		
Test point level	Forward & reverse		-dB	20.0	
Test point accuracy	Forward & reverse		±dB	0.75	
<b>Station Slope</b>				MB (Mini Bridger)	BLE (Line Extender)
Operational slope (Tilt)	@ 105 / 550 / 1218 MHz		dB	0 / 7.2 / 18.0	0 / 7.2 / 18.0
Slope control type	Cable equalizers		dB	Pad Adjustable EQ's	
Slope control range	Includes cable equivalent		dB	-12.0 to +22.0	
Slope control steps	Equalizer value steps		dB	1.0	
<b>Station Group Delay</b>					
Group delay	Channel A-2			30	
Group delay	Channel A-1		nSec /	16	
Group delay	Channel 14		3.58 MHz	10	
Group delay	Channel 15 & up			3	
<b>AGC</b>					
DSIM-A Single Pilot Channel AGC					
Pilot channel type	Up to 1002 MHz		N / A	Analog or QAM	
Compensation range			dB	System compensation input change +4/-8 @ 1218 MHz	
Accuracy			±dB	0.5	
Nominal loss	@ 77 °F (25 °C)		dB	6.25	
<b>Configuration</b>				MB (Mini Bridger)	BLE (Line Extender)
<b>Operational Specifications</b>					
Station flatness	Normalized w/ 0 dB slope		±dB	0.50	0.35
Gain - Port 2 (W/DSIM)	+1.0 / -0 @ 1218 MHz		dB	48.0	42.0
Gain - Port 3 (W/DSIM)			dB	-	-
Gain - Port 4 (W/DSIM)			dB	48.0	-
442 MHz analog channel loading, 74 channels + 660 MHz digital channel loading, 256 QAM at -6 dBc relative to its associated visual carrier					
<b>Station Referenced Output Levels</b>				MB (Mini Bridger)	BLE (Line Extender)
Port 2	@ 105 / 550 / 1218 MHz		dBmV	39.0 / 46.2 / 57.0	39.0 / 46.2 / 57.0
Port 3			dBmV	-	-
Port 4			dBmV	39.0 / 46.2 / 57.0	-
Reference output slope (Tilt)	105-1218 MHz		dB	18.0	18.0
<b>Station Noise Figure</b>					
Noise figure (W/1 dB for input EQ loss)	Typ. @ 105 to 1002 MHz		dB	9.0	9.0
	Typ. @ 1218 MHz		dB	9.5	10.5
<b>Station Distortions (Worse Case)</b>					
Composite Triple Beat (CTB)			-dBc	67	67
Cross Modulation (XMOD)			-dBc	65	64
Composite Second Order (CSO-)	(Vc +0.75 & -1.25 MHz)		-dBc	67	67
Composite Second Order (CSO+)	(Vc +1.25 MHz)		-dBc	67	67
MER			dB	≥40	≥40
BER			N / A	≤ 1 x 10 <sup>-9</sup>	≤ 1 x 10 <sup>-9</sup>

# Station Parameters 204/258

STATION PARAMETERS:		1218 MHz 204-258 MHz Split		ASEM For Motorola 1218 MHz MB & BLE	
		CONDITIONS	UNITS	SPECIFICATIONS	
Housing passband			MHz	5 to 1218	
Input current capacity	Any port, worst case		Amp	15	
Hum modulation	Time domain @ rated current above		-dBc	65 @ 5-204 MHz 65 @ 258-1218 MHz	
Return loss	Any port, worst case		dB	16.0	
<b>Test Points</b>					
Frequency range			MHz	5 to 204 (Reverse) / 258 to 1218 (Forward)	
Test point type	Directional coupler		N / A		
Test point level	Forward & reverse		-dB	20.0	
Test point accuracy	Forward & reverse		±dB	0.75	
<b>Station Slope</b>				<b>MB (Mini Bridger)</b>	<b>BLE (Line Extender)</b>
Operational slope (Tilt)	@ 258 / 550 / 1218 MHz		dB	0 / 4.7 / 15.5	0 / 4.7 / 15.5
Slope control type	Cable equalizers		dB	Pad Adjustable EQ's	
Slope control range	Includes cable equivalent		dB	-12.0 to +22	
Slope control steps	Equalizer value steps		dB	1.0	
<b>Station Group Delay</b>					
Group delay	Channel 30			30	
Group delay	Channel 31		nSec /	16	
Group delay	Channel 32		3.58 MHz	10	
Group delay	Channel 33 & up			3	
<b>AGC</b>					
DSIM-A Single Pilot Channel AGC					
Pilot channel type	Up to 1002 MHz		N / A	Analog or QAM	
Compensation range			dB	System compensation input change +4/-8 @ 1218 MHz	
Accuracy			±dB	0.5	
Nominal loss	@ 77 °F (25 °C)		dB	6.25	
<b>Configuration</b>				<b>MB (Mini Bridger)</b>	<b>BLE (Line Extender)</b>
<b>Operational Specifications</b>					
Station flatness	Normalized w / 0 dB slope		±dB	0.50	0.35
Gain - Port 2 (W/DSIM)	+1.0 / -0 @ 1218 MHz		dB	48.0	42.0
Gain - Port 3 (W/DSIM)			dB	-	-
Gain - Port 4 (W/DSIM)			dB	48.0	-
<b>Station Referenced Output Levels</b>				<b>MB (Mini Bridger)</b>	<b>BLE (Line Extender)</b>
Port 2	@ 258 / 550 / 1218 MHz		dBmV	41.5 / 46.2 / 57.0	41.5 / 46.2 / 57.0
Port 3				-	-
Port 4				41.5 / 46.2 / 57.0	-
Reference output slope (Tilt)	258-1218 MHz		dB	15.5	15.5
<b>Station Noise Figure</b>					
Noise figure (W/1 dB for input EQ loss)	Typ. @ 258 to 1002 MHz		dB	9.0	9.0
	Typ. @ 1218 MHz		dB	9.5	10.5
<b>Station BER/MER Performance</b>					
MER			dB	≥40	≥40
BER			N / A	≤ 1 x 10 <sup>-9</sup>	≤ 1 x 10 <sup>-9</sup>

# Reverse Spectrum

REVERSE SPECTRUM:			ASEM For Motorola 1218 MHz MB & BLE	
<b>REVERSE</b>				
<b>Reverse - General</b>		<b>CONDITIONS</b>	<b>UNITS</b>	
Station passband			MHz	5 to 42, 5 to 85, 5 to 204
Station flatness - 5 to 42 MHz	Normalized w / 0 dB slope	±dB		0.50
Station flatness - 5 to 85 MHz	Normalized w / 0 dB slope	±dB		0.50
Station flatness - 5 to 204 MHz	Normalized w / 0 dB slope	±dB		0.65
<b>Reverse - Station Gain</b>				
Gain	+1.0 / -0 @ HF		dB	28.0
Gain control type				JXP Plug-in pads
<b>Reverse - Station Slope</b>				
Slope control type	Cable equalizers		N / A	Pad Adjustable Eqs
Slope control range			dB	0 to 15.0
Slope control steps	Equalizer value steps		dB	1.0
<b>Reverse - Station Group Delay</b>				
Group delay	5 MHz	nSec / 1.5 MHz		45
Group delay	7 MHz			16
Group delay	10 MHz			5
Group delay	35 / 80 / 199 MHz			10
Group delay	38.5 / 83.5 / 202.5 MHz			25
<b>Configuration</b>			<b>MB (Mini Bridger)</b>	<b>BLE (Line Extender)</b>
<b>Reverse - Station Dynamic Range</b>				
Reference Output Level			dBmV	42.0
NPR at 50 dB CNR at 42 MHz	42/53 Split		dB	21.0
NPR at 50 dB CNR at 85 MHz	85/105 Split		dB	18.0
NPR at 50 dB CNR at 204 MHz	204/258 Split		dB	12.0
<b>Reverse - Noise Figure</b>				
Noise figure (W/1 dB for input EQ loss)	42/53 Split		dB	11.5
	85/105 Split		dB	11.5
	204/258 Split		dB	11.5
<b>Power Requirements:</b>				
Max Watts	Includes reverse & DSIM (Worst case)		W	42.9
<b>AC Voltage</b>				
Input ranges			VAC	45 to 90
<b>Current Draw (with DSIM AGC)</b>				
@ 45 VAC	Maximum		A	1.28
@ 50 VAC			A	1.15
@ 60 VAC			A	1.07
@ 70 VAC			A	0.93
@ 80 VAC			A	0.81
@ 90 VAC			A	0.74
<b>Weight</b>				
Weight			lbs. (kg)	3.75 (1.7)
<b>Physical</b>				
Dimensions	(H X W X D)		In, (cm)	5.9 X 12.6 X 2.36 (15 X 32 X 6)
<b>Environmental</b>				
Operating temperature			°F (°C)	-40 to +140 (-40 to +60)

## Accessory Ordering Information:

The ASEM Moto ordering matrix provides the part number information to order the configured stations. This page contains the ordering information for the required accessories that will be needed to make the stations functional in the field or the optional accessories that can be ordered separately.

### Required Accessories

Description	Part Numbers (Where XX = dB value)
JXP style attenuator pads <ul style="list-style-type: none"> <li>• 1 Required for forward input</li> <li>• 1 Required for reverse output</li> <li>• 1 Required for forward input Equalizer</li> <li>• 1 Required for reverse output Equalizer</li> </ul>	JXP137B-XX (0 to 20 dB in 1.0 dB steps)

### Optional Accessories

Description	Part Numbers
Digital Station Intelligence Manager - Single Pilot AGC Module (Analog or Digital)	DSIM-A-MDL-1201
Digital Station Intelligence Manager -Controller	DSCT-xxx-yyy xxx = Pilot Channel Number yyy = Channel Type IRC = Analog IRC Spacing DIG = Digital / QAM
DSIM Bluetooth Dongle Apple iOS or android	DSIM-DONGLE-02
Cable assembly DSIM adaptor to connect controller	240330-01
Pad Adjustable Equalizer JXP Platform 0-22 dB	AEQ1.2G
Pad Adjustable Cable Equivalent Equalizers Low Range 1-8 dB Pad Adjustable Cable Equivalent Equalizers High Range 9-15 dB	ACEQ1.2G ACEQH1.2G
Pad Adjustable Reverse Equalizers 5-42, 85 and 204 MHz JXP Platform 0-12 dB (5 Pin)	AREQPE42 AREQPE85 AREQPE204
Motorola MB DC/SP2 For P3 or P4	SDA1.2-SPLT SDA1.2-DC8 SDA1.2-DC10 SDA1.2-DC12
Test Probe (5.5" Long)	100685-01
Test Probe (1.57" / 4 cm Long)	TP-7504
Seizure 15 Amp Red 15 Amp Housing for Motorola MB (QTY 4)	120578-04
Seizure 15 Amp White 15 Amp Housing Motorola BLE (QTY 2)	120636-02
Split Conversion Kit, Moto MB 85/105 1.2G 18 dB Slope	120620-01
Split Conversion Kit, Moto BLE 85/105 1.2G 18 dB Slope	120619-01
Split Conversion Kit, Moto BLE 85/105 1.2G 11 dB Slope	120662-01
Split Conversion Kit, Moto MB 204/258 1.2G 15.5 dB Slope	120622-01
Split Conversion Kit, Moto BLE 204/258 1.2G 15.5 dB Slope	120621-01
Split Conversion Kit, Moto BLE 204/258 1.2G 8.5 dB Slope	120663-01
Moto MB 45-90 VAC Power Supply for Jerrold Housings	MB-MPPS
Moto MB 45-90 VAC Power Supply for GI/Motorola Housings	MB-MPPS-II

Description	Part Numbers
Moto MB 45-90 VAC Power Supply for ACI Housings	MB-MPPS-III
Moto MB ACI Housing With 45-90VAC Power Supply	HSG01-MB-PS
Moto BLE ACI Housing	HSG01-BLE



# Ordering Matrix

<b>ASEM™ 1.2G Moto Product Configuration Worksheet</b>																										
Customer: _____																										
Created By: _____						Order Date: _____																				
<b>ORDERING MATRIX</b>											January 25, 2023															
Position	1	2	3	4	5	6	7	8	9	10	11															
PART NUMBER																										
1,2	<input type="checkbox"/>	<input type="checkbox"/>	STATION TYPE																							
BL = 1 Output LE      MB = 2 or 3 Output Bridger																										
3	<input type="checkbox"/>	BANDWIDTH FREQUENCY																								
2 = 1218 MHz Upper Frequency																										
4	<input type="checkbox"/>	BANDPASS SPLIT																								
K = 5-42 MHz / 54- 1218 MHz MHz      H = 5-204 MHz / 258-1218 MHz N = 5-85 MHz / 105-1218 MHz MHz																										
5,6	<input type="checkbox"/>	<input type="checkbox"/>	STATION GAIN (Forward)																							
Amplifier Model																										
Max gain with DSIM-A AGC																										
		BL	MB																							
		42	48																							
7	<input type="checkbox"/>	FORWARD GAIN CONTROL TYPE																								
D = Digital Station Intelligence Manger (DSIM-A)																										
8	<input type="checkbox"/>	STATION SLOPE																								
<table border="1" style="width: 100%; border-collapse: collapse; text-align: center;"> <thead> <tr style="background-color: #ffff00;"> <th style="width: 10%;"></th> <th style="width: 15%;">Type</th> <th style="width: 15%;">54-1218</th> <th style="width: 15%;">105-1218</th> <th style="width: 15%;">258-1218</th> </tr> </thead> <tbody> <tr> <td>V =</td> <td>MB or BLE</td> <td>19.0</td> <td>18.0</td> <td>15.5</td> </tr> <tr> <td>W =</td> <td>BLE Only</td> <td>12.0</td> <td>11.0</td> <td>8.5</td> </tr> </tbody> </table>													Type	54-1218	105-1218	258-1218	V =	MB or BLE	19.0	18.0	15.5	W =	BLE Only	12.0	11.0	8.5
	Type	54-1218	105-1218	258-1218																						
V =	MB or BLE	19.0	18.0	15.5																						
W =	BLE Only	12.0	11.0	8.5																						
9	<input type="checkbox"/>	STATION GAIN (Reverse)																								
L = 28 dB																										
10	<input type="checkbox"/>	HOUSING OPTIONS																								
M = RF Module Only C = Complete Station With Housing																										
11	<input type="checkbox"/>	CUSTOM OPTIONS																								
0 = NONE X = Determined by Product Management																										
Generic Order Form: Not all configurations are available																										

**ACI**<sup>®</sup>  
 ACI Communications, Inc.  
 23307 66th Avenue South  
 Kent, WA 98032

Rev N 02-01-2024 Printed in U.S.A.  
 ACI Communications, Inc. reserves the right to discontinue the manufacture or change specifications without prior notice on any parts illustrated in this data sheet. ACI and DSIM are registered trademarks and ASEM and ACION are trademarks of ACI. Other trademarks are the property of their respective owners, and ACI is in no way affiliated with these companies.