



## Arris®/C-COR™ 45-90 VAC 2.3 Amp Power Supply For FM901E Series AFM901E-90VPS

The Arris/C-COR FM901E series power supplies are designed to be drop-in replacements to the OEM power supplies. The power supply accepts a quasi-square wave input between 45 and 90 VAC to provide a +24 VDC 2.3 Amp output to the RF module. Built into the power supply is a triac surge protection. The power supplies can be used to power the Arris/C-COR FM901E series RF modules or the ACI ASEM 1G and 1.2G drop in upgrade modules.

## Specifications

ACI POWER SUPPLY FM901E Series		AFM901E-90VPS	
Specifications	UNITS	SPECIFICATION	
Input Voltage Range	Vrms	45 - 90	
Input Line Frequency Range	Hz	47 - 63	
Output Voltage Ranges. (For All Input Voltage Ranges and Temperatures)	Vdc	24 ± 0.5	
Output Current Range	A	0 – 2.3	
Output Ripple (pk-pk, DC~30MHz)	mV	30 Max.	
Short Circuit Duration	Time	Continuous	
Input Surge Protection Range(s). Input surge test requirement (When installed in the amplifier)- IEEE C62.41 Class B3 Combination wave using A2 OHM source impedance	Vpeak	6000 VOLT SURGE	
Efficiency at Full Load High Line (90 Vac)	%	>85	
Input Power Factor	W/VA	>0.6	
Low Voltage Cutoff "LVC"	Vrms	42 ±1.5	
Minimum Restart Voltage	Vrms	42 ±1.5	
<b>Environmental</b>			
Operating Temperature	°F (°C)	- 40 to + 185 (- 40 to + 85)	



ACI Communications, Inc.  
23307 66th Avenue South  
Kent, WA 98032

Rev B 01-17-2023 Printed in U.S.A.  
ACI Communications, Inc. reserves the right to discontinue the manufacture or change specifications without prior notice on any parts illustrated in this data sheet. ACI and DSIM are registered trademarks and ASEM and ACION are trademarks of ACI. Other trademarks are the property of their respective owners, and ACI is in no way affiliated with these companies.